

January 29, 2021

#### Introduction

On 29 March 2014, the Directive 2014/34/EU (commonly referred to as "ATEX") of the European Parliament was issued regarding potentially explosive atmospheres. Advanced Pressure Technology ("AP Tech") manufactures pressure regulators that could be installed in such environments.

#### Why Explosion Protection for Pressure Regulators?

In the event of a leak in a flammable gas piping system, a potentially explosive atmosphere can envelop the pressure regulator. While many existing standards and regulations concern electrical components and electrical equipment used in these applications, ATEX requires that all components and equipment be evaluated. AP Tech pressure regulators are considered *components*. Based on the ATEX Directive, AP Tech considers the location where the pressure regulators are installed to be classified Equipment-group II, Category 3 because flammable gases would only be present for a short period of time in the event of a leak. It is possible that the location could be classified Equipment-group II, Category 2 if a leak is likely to occur. Please note that the system owner, not AP Tech, is responsible for determining the classification of a particular installation.

#### **Product Assessment**

AP Tech performed a conformity assessment and risk analysis of its pressure regulator models and their common options, with respect to the Essential Health and Safety Requirements in Annex II of the ATEX directive. The details of the assessment in terms of the individual Essential Health and Safety Requirements are listed in Appendix A. The tables in Appendix B list all of the models and options that were evaluated and along with their evaluation. The first table in Appendix B is for diaphragm regulators. The second table is for piston regulators. Models and options not listed in Appendix B should be assumed to not have been evaluated and therefore should not be selected for use in a potentially explosive environment until they have been evaluated.

Standard default options for each listed model were evaluated even if they were not explicitly listed as a separate option in the table. For example, the standard seat material for an AP1500 model regulator is PCTFE, and as a result the PCTFE seat was evaluated for this model even though PCTFE was not listed as a seat material option in the table. Not all options listed in the tables are available to all models listed in the tables.

When specifying a regulator that is to be used in a potentially explosive environment one must review the evaluations in Appendix B for the specific model and each and every option that is being specified, in order to determine the complete assessment for the regulator.

A summary of the models and options found to have an impact on ATEX assessment due to potential ignition sources or other concerns from the ATEX Essential Health and Safety Requirements, are listed below.

- 1. The plastic Nylon 6, 30-33% glass filled knob used as standard on models AP1000/AK1000/AZ1000, AK1000T, AP1100/AK1100/AZ1100, AP1200/AK1200/AZ1200, AP1300/AK1300/AZ1300, AP1400T/AK1400T/AZ1400T, AP1500/AK1500/AZ1500, AP1600, AP1700/AK1700, AP1900, AP2700, AK100, AP500, AK8000, AZ9200, BP1000, KT8, KT9, SL5400, SL5500, and SL5800, has been tested in accordance with IEC:2004 60079-0 Section 26.14 and confirmed to not be an ignition source due to static build up. To eliminate the plastic knob, the machined knob (MK) option, the pneumatic actuator (PA), and the preset outlet pressure options are available for most models.
- 2. The pressure gauges offered as options on most of the regulator models and as standard components for crossover regulator manifold models, use a plastic polycarbonate window that is a potential ignition source due to static electricity discharge. To demonstrate that the gauges are not a potential source of ignition, the gauges would need to be tested to determine if a transferred charge is below the acceptable values in IEC 60079-0 Section 26.14 or the pressure gauge supplier must provide documentation indicating the gauge is compliant with the ATEX Directive (See items 26, 27, and 28 in Appendix A). Until compliance is determined, regulators should not be ordered with pressure gauges for use in potentially explosive environments.
- 3. AP M60/AK M60, AP M66/AK M66, and AK M80 crossover manifold models are only offered from the factory with pressure gauges. Since the compliance of pressure gauges is undetermined at this time (see item 2 above), the AP M60/AK M60, AP M66/AK M66, and AK M80 models should not be specified for use in potentially explosive environments.
- 4. Tied diaphragm regulators with outlet ranges greater than 100 psig should be preset to minimize the risk that improper operation might lead to an outboard leak and a potentially explosive atmosphere (See item 6 in Appendix A).
- 5. KT9, KT10, and KT12 regulators <u>must be ordered with the non-relieving option (instead of the self relieving option)</u> if the process gas they are to be used with is hazardous (flammable, toxic, etc.). The self-relieving option vents process gas through the regulator cap directly into the atmosphere while the non-relieving option does not. Using a KT9, KT10, or KT12 with the self-relieving option in a flammable gas system could create an explosive atmosphere in the vicinity of the regulator.
- 6. Regulators with customer supplied parts are assumed to not have been evaluated in regard to ATEX and thus are not to be used in a potentially explosive environment unless a documented evaluation for the specific customer supplied parts in question has been made. Refer to Appendix B for all models and options that have been evaluated.

#### **Product Usage**

A summary of ATEX related usage issues that were found in the assessment are listed below.

1. Pressure regulators must be grounded (earthed) to prevent static charge build-up due to the flowing media. The regulator can be grounded through the mounting holes on the bottom of the body or the system piping can be grounded and electrical continuity verified through the body metal face seal connections. Grounding of the regulator should follow the same requirements for the piping system. Also see item 30 in Appendix A.

- 2. The system designer and users must take precautions to prevent rapid system pressurization which may raise surface temperatures of system components and tubing due to adiabatic compression of the system gas.
- 3. Heating systems installed by the user could possibly increase the surface temperature and must be evaluated by the user for compliance with the ATEX Directive. User installation of heating systems applied to the regulator body or system piping that affects the surface temperature of the pressure regulator is outside the scope of this declaration and is the responsibility of the user.
- 4. The Joule-Thomson effect may cause process gases to rise in temperature as they expand going through a regulator. This could raise the external surface temperature of the regulator body and downstream piping creating a potential source of ignition. Whether the Joule-Thomson effect leads to heating or cooling of the process gas depends on the process gas and the inlet and outlet pressures. The system designer is responsible for determining whether the process gas temperature may rise under any operating conditions. If a process gas temperature rise is possible under operating conditions, then the system designer must investigate whether the regulator body and downstream piping may increase in temperature enough to create a potential source of ignition.

The process gas expansion is typically modeled as a constant enthalpy throttling process for determining the temperature change. A Mollier diagram (Pressure – Enthalpy diagram with constant temperature, density, & entropy contours) or a Temperature – Entropy diagram with constant enthalpy lines, for the process gas, can be used to determine the temperature change. Helium and hydrogen are two gases that typically increase in temperature when expanding across a regulator. Other gases may increase in temperature at sufficiently high pressures.

If the above issues are addressed by selecting options that do not have potential sources of ignition, avoiding options that have not been assessed, and by taking the proper usage issue precautions, then the AP Tech regulator can be considered to be a mechanical device that does not have its own source of ignition and thus falls outside the scope of the ATEX directive.

#### **Product Declaration**

AP Tech declares that the

AP20, AP9000, AP9100, and SL5200

regulator models when specified without gauges, without options considered to have a potential source of ignition, and without unevaluated options, fall outside the scope of the ATEX directive because the products do not have their own potential source of ignition.

#### AP Tech declares that the

AP1000/AK1000/AZ1000, AK1000T, AP1100/AK1100/AZ1100, AP1200/AK1200/AZ1200, AP1300/AK1300/AZ1300, AP1400T/AK1400T/AZ1400T, AP1500/AK1500/AZ1500, AP1600, AP1700/AK1700, AP1900, AP2700, AK100, AP500, AK8000, AZ9200/AK9200, BP1000, KT8, SL5400, SL5500, and SL5800

regulator models, when specified without gauges, without options considered to have a potential source of ignition, and without unevaluated options, fall outside the scope of the ATEX directive because the products do not have their own potential source of ignition. The

AP1200/AK1200/AZ1200, AP1400T/AK1400T/AZ1400T, AP1500/AK1500/AZ1500, AP1700/AK1700, AP1900, AP2700, AZ9200, SL5400, SL5500, and SL5800

tied diaphragm models should be specified with the preset option for outlet pressures ranges greater than 100 psig.

#### AP Tech declares that the

KT9, KT10, and KT12

regulator models, when ordered with the non-relieving option or used with a non-hazardous process gas, without gauges, and without any options considered to have a potential ignition source, fall outside the scope of the ATEX directive because the products do not have their own potential source of ignition.

#### AP Tech declares that the

AP M60, AP M66, AK M80, AK M60, and AK M66

crossover regulator models are not to be used in a potentially explosive environment since they are only offered from the factory with pressure gauges which have not been evaluated to determine compliance with the ATEX directive.

Products that are outside of the scope of ATEX are not labeled with the CE mark unless covered by another European Directive.

Refer to Appendix B for the complete list of models and option AP Tech has evaluated.

#### **Conditions for use**

The product usage issues listed above in the Product Usage section of this report should be addressed for all regulators installed in potentially explosive environments.

#### Conclusion

To determine the ATEX evaluation for a regulator with a particular configuration, the specific model and options for that regulator must be reviewed in Appendix B. If the model and options are selected such that there are no potential sources of ignition or venting of flammable gases, and the usage issues listed in the Product Usage section above are addressed, then the regulator falls outside of the scope of ATEX and may be used in a potentially explosive environment. Any options that create a potential ignition source or that could create an explosive atmosphere are not to be selected for a regulator that will be used in a potentially explosive environment. Products that are outside of the scope of ATEX are not labeled with the CE mark unless covered by another European Directive.

Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
Essential Health & Safety Requirement, Annex II	Applicable to AP Tech Regulators?	Evaluation Item	
Principles of integrated explosion safety: prevent formation of explosive atmospheres (Annex II Section 1.0.1)	Yes	<ol> <li>AP Tech regulators are designed for very low outboard leakage. All regulators are leak tested prior to shipment.</li> <li>AP Tech recommends tied diaphragm regulators for high pressure flammable gases. Tied diaphragm regulators have been proven in the field and laboratory testing to reduce the risk of overpressure conditions on the low pressure side of the regulator caused by contamination at the regulating seat. Reducing overpressure conditions can reduce the risk of diaphragm failure resulting in outboard leaks.</li> <li>KT9, KT10 and KT12 regulators must be ordered with the non-relieving option (instead of the self relieving option) if the process gas they are to be used with is hazardous (flammable, toxic, etc.). The self-relieving option vents process gas through the regulator cap directly into the atmosphere while the non-relieving option does not. Using a KT9, KT10, or KT12 with the self-relieving option in a flammable gas system could create an explosive atmosphere in the vicinity of the regulator.</li> </ol>	
Principles of integrated explosion safety: prevent ignition of explosive atmospheres (Annex II Section 1.0.1)	Yes	<b>4.</b> See items 21 through 35 in this table regarding various potential ignition sources.	
Principles of integrated explosion safety: halt or limit explosion flames or pressures ignition of explosive atmospheres (Annex II Section 1.0.1)	Not applicable	5. This feature would be incorporated into the gas delivery system equipment in which the pressure regulator is installed. An example of such equipment is a source gas cylinder cabinet. AP Tech does not manufacture gas delivery systems.	
Analysis of operating faults (Annex II Section 1.0.2)	Yes	6. Closing the regulator without proper venting of downstream pressure can cause damage to high outlet pressure regulators. The operation manual cautions users on this issue. Tied diaphragm, adjustable, regulators with outlet pressure ranges above 100 psig should not be used to minimize the risk.	

<b>Table 1. Assessment of AP Tech</b>	Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
Essential Health & Safety Requirement, Annex II	Applicable to AP Tech Regulators?	Evaluation Item		
Checking and maintenance conditions (Annex II Section 1.0.3)	Yes	7. System operator should periodically monitor the regulator outlet pressure to verify that regulator is operating correctly. Automated monitoring with an alarm for high outlet pressure is recommended.		
Surrounding area conditions (Annex II Section 1.0.4)	Yes	<ul> <li>8. AP Tech pressure regulators evaluated are designed for use in ambient conditions.</li> <li>9. Regulators are sometimes heated by customers to prevent Joule Thomson effects from causing icing or other conditions. Heating systems installed by customers must consider all ATEX requirements and are the customer responsibility.</li> </ul>		
Marking (Annex II Section 1.0.5)	Not applicable. Components are not marked per Chapter II, Article 8, Section 3.	<b>10.</b> Certificate is required that declares conformity with the provisions of the ATEX Directive and stating product characteristics and how product must be incorporated into the equipment. Product Note PN 410 was created to cover this requirement.		
Instructions (Annex II Section 1.0.6)	Yes	<ul><li>11. AP Tech has operating manuals and component data sheets on website.</li><li>12. Repair instructions are available, but AP Tech recommends regulators be sent to the factory for repair.</li></ul>		
Material selection (Annex II Section 1.1)	Yes	13. AP Tech pressure regulators evaluated are made from materials that are considered compatible with gases listed in the Regulator Selection Guide. Materials of construction that contact the process gas are identified in the component data sheet. There are no predictable changes to the materials of construction while the regulator is in service that would increase the risk of an explosion.		

Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
Essential Health & Safety Requirement, Annex II	Applicable to AP Tech Regulators?	Evaluation Item	
Design and construction (Annex II Section 1.2)	Yes	<ul> <li>14. AP Tech pressure regulators evaluated are designed for very low outboard leakage. All regulators are leak tested prior to shipment.</li> <li>15. Enclosed structures are the responsibility of the user.</li> <li>16. Dust deposits on external surfaces would not cause ignition if used within operating temperature limits and regulator surfaces can be easily cleaned.</li> <li>17. Safe opening is not applicable to pressure regulators.</li> <li>18. Protection against other hazards is not applicable.</li> <li>19. Overloading of equipment is not applicable.</li> <li>20. Flameproof enclosures are not applicable.</li> </ul>	
Potential ignition sources	Depends on source	See below discussion of each source.	
Hazards from different ignition sources (Annex II Section 1.3.1)	Not applicable	<ul> <li>21. There are no sparks, flames, electric arcs, acoustic energy, optical radiation, or electromagnetic waves in AP Tech pressure regulators evaluated.</li> <li>22. High surface temperatures are possible if the user has installed heating equipment—appropriate heating equipment and proper operation is the user's responsibility.</li> <li>23. High surface temperatures are possible due to adiabatic compression caused by rapid system pressurization – the user should operate the system properly to control this ignition source.</li> <li>24. High surface temperatures of both the regulator and the downstream piping are possible due to the expanding process gas heating up as a result of the Joule-Thomson effect. Whether the Joule-Thomson effect leads to heating or cooling of the process gas depends on the process gas and the inlet and outlet pressures. It is the system designer's responsibility to determine whether Joule-Thomson heating will occur under any operating conditions. If heating does occur, the system designer must determine whether this could raise the surface temperature enough to create a potential ignition source.</li> </ul>	

Table 1. Assessment of AP Tech re	Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
Essential Health & Safety Requirement, Annex II	Applicable to AP Tech Regulators?	Evaluation Item		
Hazards from static electricity (Annex II Section 1.3.2)	Yes	25. Some regulator models use a Nylon 6 30-33% glass filled plastic knob. The knob has been tested in accordance with IEC:2004 60079-0 section 26.14 and confirmed to not build sufficient static charge to cause ignition. The total exposed knob surface area is approx 25.4 in² (16400 mm²).  26. There are pressure gauge options that use a polycarbonate window. The total exposed polycarbonate window surface area is 7.25 in² (4700 mm²).  27. Per IEC 60079 Section 7.3, the maximum allowable surface area considered to not be an ignition source without testing is 2000 mm² for Group II, Zone 1 or 2. Larger areas must be tested to determine if a transferred charge is below the acceptable values in IEC 60079-0 Section 26.14.  28. The regulator gauge polycarbonate window has been used extensively in flammable gas systems for years, but should not be used in a potentially explosive environment until tested to verify conformance to IEC 60079 Section 7.3 or certified by supplier.  29. Process gas flow through a regulator could potentially cause static charge build-up. To prevent this, pressure regulators must be grounded (earthed). A regulator can be grounded through the mounting holes on the bottom of the body or the system piping can be grounded and electrical continuity verified through the body metal face seal connections. Grounding of a regulator should follow the same requirements for the piping system.  30. Based upon the "European ATEX Guidelines for the Valve Industry", CEIR, July 2006, statement in section B.1), that "Electrostatic charges caused by the flow-through of the fluid are not to be considered as own ignition sources," AP Tech did not consider this potential ignition source to be a potential ignition source of the evaluated regulators themselves.		
Hazards from stray electric and leakage currents (Annex II Section 1.3.3)	Yes	<ul><li>31. AP Tech pressure regulators evaluated do not have electrical components.</li><li>32. Optional pressure switches and transmitters contain electrical parts. These parts have not been evaluated by the supplier and therefore should not be used in a potentially explosive atmosphere.</li></ul>		

Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
Essential Health & Safety Requirement, Annex II	Applicable to AP Tech Regulators?	Evaluation Item	
Hazards from overheating (Annex II Section 1.3.4)	No	<b>33.</b> AP Tech pressure regulators evaluated are adjusted slowly by hand and with low friction loads so that heat buildup is virtually impossible.	
Hazards from pressure compensation operations (Annex II Section 1.3.5)	No	<b>34.</b> Operation of AP Tech regulators does not cause shock waves or compressions that could ignite an explosive atmosphere outside the regulator.	
Hazards arising from external effects (Annex II Section 1.4)	Yes	<b>35.</b> AP Tech pressure regulators evaluated are designed to withstand the intended application.	
Requirements of safety related devices (Annex II Section 1.5)	Not applicable.		
Integration of safety requirements related to the system (Annex II Section 1.6)	Not applicable.		
Requirements of category M equipment (Annex II Section 2.0)	Not applicable	<b>36.</b> AP Tech pressure regulators evaluated are installed in Group II, category 2 or Group II, category 3 locations.	
Requirements of category 1, Group II equipment (Annex II Section 2.1)	Not applicable	<b>37.</b> AP Tech pressure regulators evaluated are installed in Group II, category 2 or Group II, category 3 locations.	
Requirements of category 2, Group II equipment (Annex II Section 2.2.1)	Yes	<ul> <li>38. Potential ignition sources are addressed in items 21 through 35 above. No additional ignition sources that could be caused by frequently occurring disturbances or faults were identified.</li> <li>39. Potential causes of increased surface temperature are addressed in items 22 through 24 above.</li> <li>40. Opening of parts is not applicable to components.</li> </ul>	
Requirements of category 2, Group II equipment (Annex II Section 2.2.2)	No	<b>41.</b> AP Tech pressure regulators evaluated are not intended for installation in air/dust mixtures.	

Table 1. Assessment of AP Tech regulators in terms of the individual ATEX Essential Health and Safety Requirements			
<b>Essential Health &amp; Safety</b>	Applicable to AP Tech Evaluation Item		
Requirement, Annex II	Regulators?		
Requirements of category 3, Group	Yes	<b>42.</b> Potential ignition sources are addressed in items 21 through 35 above.	
II equipment		<b>43.</b> Potential causes of increased surface temperature are addressed in items 22	
(Annex II Section 2.3.1)		through 24 above.	
Requirements of category 2, Group	No	<b>44.</b> AP Tech pressure regulators evaluated are not intended for installation in	
II equipment		air/dust mixtures.	
(Annex II Section 2.3.2)			
Requirements for protective	Not applicable.		
systems			
(Annex II Section 3)			

Option			
Category Category	Option	Designator	<b>Evaluation Item</b>
Model	AP1000/AK1000/AZ1000	AP10/AK10/AZ10	<b>45.</b> Users who prefer to eliminate the plastic knob may
	AK1000T	AK10 T	order the machined metal knob (MK), preset (PS), or
	AP1100/AK1100/AZ1100	$AP11/\overline{A}K11/AZ11$	pneumatic actuation (PA) option, if available.
	AP1200/AK1200/AZ1200	AP12/AK12/AZ12	, , , -
	AP1300/AK1300/AZ1300	AP13/AK13/AZ13	
	AP1400T/AK1400T/AZ1400T	AP14T/AK14T/AZ14T	
	AP1500/AK1500/AZ1500	$AP15\overline{/}AK15\overline{/}AZ\overline{15}$	
	AP1600	AP16	
	AP1700/AK1700	AP17/AK17	
	AP1900	AP19	
	AP2700	AP27	
	AK100	AK1	
	AP500	AP5	
	AK8000	AK80	
	AZ9200/AK9200	AZ92/AK92	
	BP1000	BP1000	
	KT8	KT8	
	SL5400	SL54	
	SL5500	SL55	
	SL5800	SL58	
	AP20	AP20	<b>46.</b> These models have a metal knob as standard.
	AP9000/AP9100	AP90/AP91	
	SL5200	SL52	
	AP M60/AK M60	AP M60/AK M60	<b>47.</b> These models are only sold with pressure gauges
	AP M66/AK M66	AP M66/AK M66	included and therefore are not to be used in potentially
	AK M80	AK M80	explosive environments. See items 26,27, and 28 in
			Appendix A.

Table 2. Diaphragm Regulator Options Evaluated in Regard to ATEX			
Option		· ·	
Category	Option	Designator	Evaluation Item
Maximum	10 psig	01	<b>48.</b> Does not affect ATEX evaluation.
Outlet Pressure	30 psig	02	
Rating	60 psig	06	
	100 psig	10	
	120 psig	12	<b>49.</b> The preset outlet pressure option (PS) is recommended
	150 psig	15	for maximum outlet pressure ratings greater than 100 psig
	200 psig	20	to help prevent improper operation that could damage the
	250 psig	25	diaphragm and cause an outboard leak. See item 2 in
	300 psig	30	Appendix A. This does not apply to free poppet and
	500 psig	50 or F	BP1000 regulators.
	1500 psig	J	
Body Material	Stainless	S	<b>50.</b> Does not affect ATEX evaluation.
	Hastelloy C-22	Н	
	Brass	В	
Surface Finish	10 Ra	M	<b>51.</b> Does not affect ATEX evaluation.
	7 Ra	V	
	5 Ra	X	
Hastelloy	Hastelloy C-22 Poppet	Н	<b>52.</b> Does not affect ATEX evaluation.
Internal Parts	Hastelloy C-22 Poppet &	HP	
	Diaphragm		
	Hastelloy C-22 Nozzle, Poppet,	H	
	& Diaphragm		
	Hastelloy Diaphragm	HD	
Absolute Inlet	Absolute Inlet Pressure	A	<b>53.</b> Does not affect ATEX evaluation.
Pressure			
Left Hand Inlet	Left Hand Inlet	L	<b>54.</b> Does not affect ATEX evaluation.

Table 2. Diaph	Fable 2. Diaphragm Regulator Options Evaluated in Regard to ATEX				
Option					
Category	Option	Designator	<b>Evaluation Item</b>		
Porting		2PW, 2PWA, 2PWC	<b>55.</b> Does not affect ATEX evaluation.		
Configuration		3PW, 3PWJ			
		4PW, 4PWA, 4PWC, 4PWK, 4PWL,			
		4PWN, 4PW6			
		5PW, 5PWC, 5PWCS, 5PW6			
Fittings/Ports	Male Face Seal Fittings	MV4, MV6, MV8, MV12, MV16	<b>56.</b> Does not affect ATEX evaluation.		
	Female Face Seal Fittings	FV4, FV6, FV8, FV12, FV16			
	Tube Stubs	TW4, TW8, TW12, TW16			
	Internal Face Seal Fittings	IV4			
	Face Seal Fitting Elbows	MVE4, FVE4			
	O-ring Face Seal Fittings	MC4, MC6, FC4, FC6			
	NPT Ports	4, 6, 8, 12, 16			
	Tube Compression Fittings	4T, 6T, 6MT			
CGA Fittings	Inlet Port Gas Cylinder Fittings	CGA	<b>57.</b> Does not affect ATEX evaluation.		
		170/180/296/300/320/326/330/346/35			
		0/510/540/580/590/632/634/638/640/6			
		42/660/670/678/679/705/712/716/718/			
		720/724/728			

Table 2. Diaphi	Table 2. Diaphragm Regulator Options Evaluated in Regard to ATEX			
Option				
Category	Option	Designator	Evaluation Item	
Gauges	30"-0 psig/bar	V	<b>58.</b> Pressure gauges are not to be selected as options on	
	30"-0-15 psig/bar	V15	components for use in potentially explosive environments.	
	30"-0-30 psig/bar	V3	See items 26, 27, and 28 in Appendix A.	
	30"-0-60 psig/bar	L		
	30"-0-100 psig/bar	1		
	30"-0-160 psig/bar	H		
	30"-0-200 psig/bar	V2		
	30"-0-300 psig/bar	D		
	0-15 psig/bar	X15		
	0-30 psig/bar	VX		
	0-60 psig/bar	LX		
	0-100 psig/bar	1X		
	0-160 psig/bar	G		
	0-200 psig/bar	2		
	0-400 psig/bar	4		
	0-600 psig/bar	K		
	0-1000 psig/bar	10		
	0-2000 psig/bar	20		
	0-3000 psig/bar	30		
	0-4000 psig/bar	40		
Cap or Plug	Cap or Plug on Ports/Fittings	C	<b>59.</b> Does not affect ATEX evaluation.	
Seat Material	Teflon PFA	PF	<b>60.</b> Does not affect ATEX evaluation.	
(excluding	Teflon PTFE	TF		
BP1000)	Vespel SP-1	VS		
	Kynar	KN		
	Peek	PK		
Seat Material	Kalrez	KZ	<b>61.</b> Does not affect ATEX evaluation.	
(BP1000 only)	Teflon PTFE	TF		
High Flow	High Flow Seat & Poppet	HF	<b>62.</b> Does not affect ATEX evaluation.	
Inlet Filter	No Filter Under Poppet	NF	<b>63.</b> Does not affect ATEX evaluation.	

Table 2. Diap	hragm Regulator Options Eval	uated in Regard to ATEX	
<b>Option</b>			
Category	Option	Designator	<b>Evaluation Item</b>
Knob	Metal Knob	MK	<b>64.</b> This option replaces the plastic Nylon 6 30-33% glass
			filled knob with a conductive, machined, metal knob.
Cap Options	Short Cap	SC	<b>65.</b> Does not affect ATEX evaluation.
	Panel Mount	P	
	Preset Outlet Pressure	PS	<b>66.</b> This option is recommended for outlet pressures
			ratings greater than 100 psig (excluding BP1000 models)
			to help prevent improper operation that could damage the
			diaphragm and cause an outboard leak.
			<b>67.</b> This option eliminates the knob.
	Force Compensator	FC	<b>68.</b> Does not affect ATEX evaluation.
	Pneumatic Actuator	PA	<b>69.</b> This option eliminates the knob.
High Inlet	High Inlet Pressure Rating	HR	<b>70.</b> Does not affect ATEX evaluation.
Pressure Ratin	g		
Customer	Customer Supplied Parts	CSP	71. Customer supplied parts should be assumed to have not
Supplied Parts			been evaluated by AP Tech in regard to ATEX unless AP
			Tech has explicitly made an evaluation for the specific
			parts.

<b>Piston Regulato</b>	Piston Regulator Options Evaluated in Regard to ATEX			
Option				
Category	Option	Designator	Evaluation Item	
Models	KT9	KT9	<b>72.</b> Plastic Nylon 6 30-33% knob is standard	
	KT10	KT10	<b>73.</b> These models have a metal knob as standard.	
	KT12	KT12		
Maximum	120 psig	В	74. Does not affect ATEX evaluation.	
Outlet Pressure	200 psig	D		
Rating	500 psig	F		
	600 psig	G		
	800 psig	H		
	1000 psig	I		
	1500 psig	J		
	2500 psig	L		
	4000 psig	N		
	6000 psig	P		
	10 000 psig	R		
Cap Assembly	Non-Self Relieving	0	<b>75.</b> KT9, KT10, and KT12 regulators must be ordered with	
	Pneumatic Actuation (Non-Self	2	one of these two options if the process gas is hazardous	
	Relieving)		(toxic, flammable, etc.). Item 3 in Appendix A. (KT9 not	
			available with pneumatic actuation.)	
	Self Relieving	1	<b>76.</b> KT9, KT10, and KT12 regulators must <b>not</b> be ordered	
			with this option if the process gas is hazardous (toxic,	
			flammable, etc.)	
Body Material	303/304 Stainless	С	77. Does not affect ATEX evaluation.	
	Brass	В		
	316 Stainless (Welded Fittings)	S		

Piston Regulator Options Evaluated in Regard to ATEX			
Option			
Category	Option	Designator	Evaluation Item
Porting	Porting Configuration	2P	<b>78.</b> Does not affect ATEX evaluation.
Configuration		4P	
		4PN	
		4PQ	
		4PW	
Ports/Fittings	NPT Ports	4, 6, 8, 12	<b>79.</b> Does not affect ATEX evaluation.
	MS33649 Boss Fittings	4B	
	Face Seal Fittings	MV4, FV4	
Gauges	600 psig	6	<b>80.</b> Pressure gauges should not be selected as options on
	1000 psig	10	components for use in potentially explosive environments.
	2000 psig	20	See items 26, 27, and 28 in Appendix A.
	4000 psig	40	
	6000 psig	60	
	10 000 psig	Q	
High Flow	High Flow Capacity	HF	<b>81.</b> Does not affect ATEX evaluation.
Seat Material	PEEK Seat	PK	<b>82.</b> Does not affect ATEX evaluation.
O-ring Material	Polyurethane	UE	<b>83.</b> Does not affect ATEX evaluation.
	Buna-N	BN	
	Ethylene Propylene	EP	
Panel Mount	Panel Mount	P	<b>84.</b> Does not affect ATEX evaluation.